

Ustawienia systemowe

Ustawienia CAN

Node-ID

Bit rate

| | | | | | | | | | |
|----------------------------------|---------------|---------------|---------------|---------------|---------------|---------------|-----------|----------|------------|
| ON | | | | | | | ON | | |
| | | | | | | | | | |
| 1 | 2 | 3 | 4 | 5 | 6 | 7 | 1 | 2 | |
| 1 - 127 | | | | | | | off | off | 50 kbit/s |
| 1 | 0 | 0 | 1 | 0 | 0 | 1 | off | on | 125 kbit/s |
| $1 \cdot 2^0$ | $0 \cdot 2^1$ | $0 \cdot 2^2$ | $1 \cdot 2^3$ | $0 \cdot 2^4$ | $0 \cdot 2^5$ | $1 \cdot 2^6$ | on | off | 250 kbit/s |
| 1 + 0 + 0 + 8 + 0 + 0 + 64 | | | | | | | on | on | 500 kbit/s |
| Node-ID: 73 _{dec} (49h) | | | | | | | | | |

jasność świecenia diod LED w panelach PWF-2

czas wyłączenia diod LED w panelach PWF-2

tryb pracy paneli PWF-2

| | | | |
|-----------|----------|----------|----------|
| ON | | | |
| | | | |
| 1 | 2 | 3 | 4 |

| | | |
|-----|-----|--------|
| on | on | — 100% |
| on | off | — 70% |
| off | on | — 40% |
| off | off | — 10% |

— on – praca z przyciskiem

— off – praca bez przycisku

czas wyłączenia 8 sekund – on

czas wyłączenia 4 sekundy – off